

Amendments to the Claims:

1. (Currently Amended) An apparatus comprising:  
a first mapper adapted to receive first representations of a first portion of communication data, said first mapper for mapping the first representations of the first portion of the communication data into first mapped values according to a first mapping scheme; and  
a second mapper adapted to receive second representations of a second portion of the communication data, said second mapper for mapping the second representations of the communication data into second mapped values according to a second mapping scheme, the second mapping scheme exhibiting a mapping property that differs with the first mapping scheme,  
wherein the first mapper transmits the first mapped values to a first antenna transducer among a plurality of antenna transducers and wherein the second mapper transmits the second mapped values to a second antenna transducer among the plurality of antenna transducers, the first and second antenna transducers receive and transduce only the first mapped values and the second mapped values, respectively, into electromagnetic form for communication upon a communication channel;- and  
wherein the apparatus defines a code comprising a plurality of layers defined over the first antenna transducer and the second antenna transducer.

2. (Original) The apparatus of claim 1 further comprising a first encoder adapted to receive the first portion of the communication data, said first encoder for encoding the first portion of the communication data according to a first encoding techniques and wherein the first representations of the first portion of the communication data to which said first mapper is adapted to receive comprise first-encoded values formed by said first encoder.

3. (Original) The apparatus of claim 1 further comprising a second encoder adapted to receive the second portion of the communication data, said second encoder for encoding the second portion of the communication data according to a second encoding technique and wherein the second representations of the second portion of the communication data to which

said second mapper is adapted to receive comprise second-encoded values formed by said second encoder.

4. (Original) The apparatus of claim 1 wherein the first mapped values into which said first mapper maps the first representations of the first portion of the communication data comprise a first set of mapped values, wherein the second mapped values into which said second mapper maps the second representations of the second portion of the communication data comprise a second set of mapped values, elements of the first set of mapped values differing in value with elements of the second set of mapped values.

5. (Original) The apparatus of claim 4 wherein the first set of mapped values and the second set of mapped values formed by said first mapper and said second mapper, respectively, are formed of mutually-exclusive elements.

6. (Original) The apparatus of claim 4 wherein the mapping property exhibited by the second mapping scheme that differs with that of the first mapping scheme comprises vector magnitudes that differ.

7. (Original) The apparatus of claim 1 wherein the first mapped values into which said first mapper maps the first representations of the first portion of the communication data comprise a first set of mapped values that exhibits first geometric differences therebetween, wherein the second mapped values into which said second representations of the second portion of the communication data comprise a second set of map values that exhibit second geometric differences therebetween.

8. (Original) The apparatus of claim 7 wherein the first geometric differences between the mapped values of the first set and the second geometric differences between the mapped values of the second set are mutually exclusive.

9. (Original) The apparatus of claim 7 wherein the mapping property exhibited by the second mapping scheme that differs with that of the first mapping scheme comprises second geometric differences that differ in lengths with lengths of the first geometric differences.

10. (Previously Presented) The apparatus of claim 1 wherein the mapping by which said first mapper maps the first representations and the mapping by which said second mapper maps the second representations are together selected to define a layered code having combined values that are applied to a respective one of the plurality of antenna transducers.

11. (Canceled)

12. (Previously Presented) In a communication system of claim 1 further having a receiving station for receiving the communication data once communicated upon the communication channel, a further improvement of apparatus for the receiving station for facilitating detection of the communication data, said apparatus comprising:

a modified maximum likelihood decoder, which exploits the difference in mapping properties between the first and second set, adapted to receive indications of the communication data communicated upon the communication channel and delivered to the receiving station, said maximum likelihood decoder for determining a maximum likelihood path that defines selection of values of the communication data, the maximum likelihood path selected from amongst a set of possible paths, each defining communication data value possibilities.

13. (Original) The apparatus of claim 12 wherein the set of possible paths from amongst which said maximum likelihood decoder selects the maximum likelihood path comprises fewer than all of the possible paths.

14. (Original) The apparatus of claim 12 wherein the set of possible paths from amongst which said maximum likelihood decoder selects the maximum likelihood path is selected responsive to at least the first mapping scheme pursuant to which said first mapper maps the first representations.

15. (Original) The apparatus of claim 14 wherein the set of possible paths from amongst which said maximum likelihood decoder selects the maximum likelihood path is further selected responsive to the second mapping scheme pursuant to which said second mapper maps the second representations.

16. (Currently Amended) A method comprising:  
mapping first representations of a first portion of communication data into first mapped values according to a first mapping scheme;  
mapping second representations of a second portion of the communication data into second mapped values according to a second mapping scheme, the second mapping scheme exhibiting a mapping property that differs with the first mapping scheme;  
selecting the first mapped values and the second mapped values; and  
transmitting only the first mapped values to a first antenna transducer among a plurality of antenna transducers and transmitting only the second mapped values to a second antenna transducer among a plurality of antenna transducers; and  
defining a code comprising a plurality of layers defined over the first antenna transducer and the second antenna transducer.

17. (Currently Amended) The method of claim 16, ~~wherein a communication system further comprises a receiving station and wherein said method further comprises: the operations of-~~ transducing the selected first mapped values and the selected second mapped values, applied during said ~~operation of~~ selecting, into electromagnetic form and delivering, by way of the communication channel, the selected first and second mapped values, respectively, to ~~the~~ a receiving station.

18. (Currently Amended) The method of claim 17 further comprising, ~~the operation of~~ decoding indications of communication data received at the receiving station, the decoding comprising determining a maximum likelihood path that defines selection of values of the

communication data, the maximum likelihood path selected from amongst a set of possible paths, each defining communication data value possibilities.

19. (Currently Amended) The method of claim 18 further comprising, ~~the operation,~~  
~~prior to said operation of decoding, of selecting the set of possible paths from which the~~  
maximum likelihood path is formable.

20. (Currently Amended) The method of claim 19 wherein the set selected during  
~~said operation of selecting the set is selected responsive to the first and second mapping schemes~~  
~~used during said operations of mapping.~~

21. (Currently Amended) An apparatus comprising:  
means for mapping first representations of a first portion of the communication data into  
first mapped values according to a first mapping scheme;  
means for mapping second representations of a second portion of communication data  
into second mapped values according to a second mapping scheme, the second mapping scheme  
exhibiting a mapping property that differs with the first mapping scheme; and  
means for selecting the first mapped values and the second mapped values and  
transmitting the first mapped values and the second mapped values to only a respective one of a  
plurality of antenna transducers, and wherein the plurality of antenna transducers transduce the  
first mapped values and the second mapped values into electromagnetic form for communication  
upon a communication channel; and  
means for defining a code comprising a plurality of layers defined over the first antenna  
transducer and the second antenna transducer.

22. (Previously Presented) The apparatus of claim 21, further comprising a means for  
receiving and encoding the first portion of the communication data, according to a first encoding  
technique to generate the first representations, the first representations comprise a first plurality  
of encoded values.

23. (Previously Presented) The apparatus of claim 21, further comprising a means for receiving and encoding the second portion of the communication data according to a second encoding technique to generate the second representations, the second representations comprise a second plurality of encoded values.

24. (Previously Presented) The apparatus of claim 1, wherein the first mapping scheme generates a first constellation set comprising a first plurality of symbol points and wherein the second mapping scheme generates a second constellation set comprising a second plurality of symbol points, wherein a first distance between each of the first plurality of symbol points is different from a second distance between each of the second plurality of symbol points.

25. (Previously Presented) The method of claim 16, wherein prior to transmitting only the first mapped values, generating, according to the first mapping scheme, a first constellation set comprising a first plurality of symbol points and generating, according to the second mapping scheme, a second constellation set comprising a second plurality of symbol points, wherein a first distance between each of the first plurality of symbol points is different from a second distance between each of the second plurality of symbol points.

26. (Previously Presented) The apparatus of claim 21, wherein the first mapping scheme generates a first constellation set comprising a first plurality of symbol points and wherein the second mapping scheme generates a second constellation set comprising a second plurality of symbol points, wherein a first distance between each of the first plurality of symbol points is different from a second distance between each of the second plurality of symbol points.

27. (Previously Presented) The apparatus of claim 1, wherein the first mapping scheme comprises a spherical modulation scheme and wherein the second mapping scheme comprises a lattice modulation scheme.

28. (Previously Presented) The method of claim 16, wherein the first mapping scheme comprises a spherical modulation scheme and wherein the second mapping scheme comprises a lattice modulation scheme.

29. (Previously Presented) The apparatus of claim 21, wherein the first mapping scheme comprises a spherical modulation scheme and wherein the second mapping scheme comprises a lattice modulation scheme.

30. (New) The apparatus of claim 1, wherein the apparatus adds each of the layers of the code to form a composite code resulting in a first time code.

31. (New) The apparatus of claim 1, wherein a first layer of the code comprises a concatenated space time block code (STBC) and a trellis code.

32. (New) The apparatus of claim 1, wherein a second layer of the code comprises a concatenated space time block code (STBC) formed by spherical modulation, wherein at least the first mapper performs the spherical modulation.

33. (New) The apparatus of claim 1, wherein the apparatus sums a first layer and a second layer of the code generating full diversity at the first and second antenna transducers.

34. (New) The apparatus of claim 33, wherein the first layer of the code comprises a low modulus property that is utilized by a receiver to generate a maximum likelihood path defining selection of values of the first and second set of values.

35. (New) The method of claim 16, further comprising adding each of the layers of the code to form a composite code resulting in a first time code.

36. (New) The method claim 16, wherein a first layer of the code comprises a concatenated space time block code (STBC) and a trellis code.

37. (New) The method of claim 16, wherein a second layer of the code comprises a concatenated space time block code (STBC) formed by spherical modulation, wherein at least the first mapper performs the spherical modulation.

38. (New) The method of claim 16, further comprising summing a first layer and a second layer of the code generating full diversity at the first and second antenna transducers.

39. (New) The method of claim 38, wherein the first layer of the code comprises a low modulus property that is utilized by a receiver to generate a maximum likelihood path defining selection of values of the first and second set of values.

40. (New) The apparatus of claim 21, further comprising means for adding each of the layers of the code to form a composite code resulting in a first time code.

41. (New) The apparatus of claim 21, wherein a first layer of the code comprises a concatenated space time block code (STBC) and a trellis code.

42. (New) The apparatus of claim 21, wherein a second layer of the code comprises a concatenated space time block code (STBC) formed by spherical modulation, wherein at least the first mapper performs the spherical modulation.

43. (New) The apparatus of claim 21, further comprising means for summing a first layer and a second layer of the code generating full diversity at the first and second antenna transducers.

44. (New) The apparatus of claim 43, wherein the first layer of the code comprises a low modulus property that is utilized by a receiver to generate a maximum likelihood path defining selection of values of the first and second set of values.